

# Xerox® VersaLink® C9000 Color Printer



The VersaLink C9000 Color Printer is built on Xerox® ConnectKey® Technology. For more information, go to [www.connectkey.com](http://www.connectkey.com).

System Specifications	VersaLink C9000DT
<b>One-Sided Speed</b> 8.5 x 11 in. / A4 8.5 x 11 in. / A4 SEF 8.5 x 14 in. / 216 x 356 mm 11 x 17 in. / A3 / 297 x 420 mm / 12 x 18 in. / SRA3 / 320 x 450 mm	Up to 55 ppm (pages per minute) long edge feed (LEF) Up to 40 ppm Up to 32 ppm Up to 27 ppm
<b>Two-Sided Speed</b> 8.5 x 11 in. / A4 8.5 x 11 in. / A4 SEF 8.5 x 14 in. / 216 x 356 mm 11 x 17 in. / A3 / 297 x 420 mm / 12 x 18 in. / SRA3 / 320 x 450 mm	Up to 55 ppm LEF Up to 40 ppm Up to 21 ppm Up to 19 ppm
<b>Monthly Duty Cycle<sup>1</sup></b>	Up to 270,000 pages / month
<b>Recommended Average Monthly Print Volume<sup>2</sup></b>	Up to 30,000 pages per month
<b>Hard Drive</b>	320 GB HDD
<b>Processor</b>	1.6 GHz Dual-Core
<b>Memory</b>	4 GB
<b>Connectivity</b>	Ethernet 10/100/1000 Base-T, High-speed USB 3.0, Wi-Fi 802.11n/g/b/a and Wi-Fi Direct with optional Wi-Fi Kit (concurrent wired and wireless connections supported), NFC Tap-to-Pair
<b>Controller Features</b>	Configuration Cloning, Xerox Extensible Interface Platform®, Xerox App Gallery, Xerox® Standard Accounting Tool, Role Based Permissions, Convenience Authentication Enabled
<b>User Interface Languages</b>	English, French, Italian, German, Spanish, Brazilian Portuguese, Russian, Dutch, Swedish, Danish, Finnish, Norwegian, Greek, Turkish, Polish, Czech, Hungarian, Romanian, Catalan

# Xerox® VersaLink® C9000 Color Printer

Device Specifications				
<b>Electrical Requirements</b>				
<b>North America</b>	Voltage: 110-127V +/-10% Frequency: 50/60 Hz +/-3%, 12A			
<b>Europe and Other Geographies</b>	Voltage: 220-240V +/- 10% Frequency: 50/60 Hz +/-3%, 10A			
<b>Power Consumption</b>				
<b>Printing<sup>3</sup></b>	For 110V: 2.85 kWh For 220V: 2.82 kWh			
<b>Standby Mode<sup>3</sup></b>	110V: 75.3 Watts or less 220V: 73.8 Watts or less			
<b>Sleep Mode<sup>3</sup></b>	110V: 0.48 watts or less 220V: 0.53 watts or less			
<b>Operating Environment</b>				
<b>Required Temperature Range (Storage)</b>	Below 48° C, and in compliance with MN2-810.13			
<b>Required Temperature Range (Operating)</b>	50° to 83° F (10° to 28° C) Must be 28° C or below if humidity is at 85 %			
<b>Required Relative Humidity</b>	15 % to 85 % Must be 62.5 % or below at 32° C			
<b>Sound Power Levels</b>	Printing: 6.83 B(A) or less Standby: 3.24 B(A) or less  <b>Full System (including finisher)</b> Printing: 7.64 B(A) Standby: 3.38 B(A)			
<b>Sound Pressure Levels</b>	Printing: 58.2 dB or less Standby: 15.1 dB or less  <b>Full System (including finisher)</b> Printing: 58.1 dB Standby: 15.3 dB			
<b>Boot Time (from Off to UI Ready)</b>	Less than 60 seconds			
<b>Warm-up Time (from Sleep to UI Ready)</b>	Less than 16 seconds			
<b>Dimensions and Weight (Unpackaged)</b>	<b>Width</b>	<b>Depth</b>	<b>Height</b>	<b>Weight</b>
VersaLink C9000/DT	24.4 in. / 620 mm	28.5 in. / 723 mm	31.9 in. / 809.3 mm	178 lb. / 80.8 kg
Two Tray Module	26.3 in. / 668.5 mm	28.5 in. / 723 mm	10.3 in. / 261.2 mm	60.0 lb. / 27.2 kg
Tandem Tray Module	26.3 in. / 668.5 mm	28.5 in. / 723 mm	10.3 in. / 261.2 mm	74.5 lb. / 33.8 kg
High Capacity Feeder	15.3 in. / 389 mm	23.7 in. / 602.9 mm	15.0 in. / 380.01 mm	63.9 lb. / 29.0 kg
Office Finisher	22 in. / 559.8 mm	21.7 in. / 552 mm	39.8 in. / 1012 mm	61.7 lb. / 28.0 Kg
Booklet Maker (Office Finisher)	11.75 in. / 298.5 mm	23.5 in. / 597 mm	42.5 in. / 1080 mm	20.3 lb. / 9.2 Kg
BR Booklet Maker Finisher	30.28 in. / 769.2 mm	28.5 in. / 723 mm	41.5 in. / 1055.1 mm	134.3 lb. / 60.9 Kg

## Xerox® VersaLink® C9000 Color Printer

Dimensions and Weight (Packaged)	Width	Depth	Height	Weight
VersaLink C9000/DT	32.8 in. / 833 mm	28.2 in. / 717 mm	33.4 in. / 852 mm	209.4 lb. / 95 kg
High Capacity Feeder	20.7 in. / 526 mm	29.8 in. / 756 mm	19.3 in. / 491 mm	74.3 lb. / 33.7 kg
Two Tray Module	32.7 in. / 830 mm	33.5 in. / 850 mm	15.75 in. / 400 mm	72.7 lb. / 33 kg
Tandem Tray Module	32.7 in. / 830 mm	33.5 in. / 850 mm	15.75 in. / 400 mm	86 lb. / 39 kg
Office Finisher	27.2 in. / 690 mm	40.2 in. / 1021 mm	25.7 in. / 654 mm	82 lb. / 37 kg
Booklet Maker Finisher	20 in. / 507 mm	30 in. / 761 mm	17.2 in. / 437 mm	31 lb. / 14 kg
BR Booklet Maker Finisher	30 in. / 764 mm	30.5 in. / 774 mm	47.4 in. / 1203 mm	169.7 lb. / 77 kg
Horizontal Transport for BR Booklet Maker Finisher	21 in. / 533 mm	23.1 in. / 589 mm	12.6 in. / 319 mm	14.3 lb. / 6.5 kg

### Certifications

To view the latest list of certifications, go to [www.xerox.com/OfficeCertifications](http://www.xerox.com/OfficeCertifications).

### Print

<b>First-print-out Time</b>	As fast as 10.5 seconds color
	As fast as 10 seconds black
<b>Print Resolution</b>	Up to 1200 x 2400 dpi
<b>Page Description Languages</b>	Adobe® PostScript® 3™ PCL® 5c, 6 PDF XPS TIFF JPEG HP-GL
<b>Color Management</b>	Embedded spot color table with the ability to swap out PANTONE® approved color table, Custom spot color editor, Xerox® Precise Color Management System software
<b>Maximum Print Area</b>	4 mm from lead edge of paper, 2 mm from Side and Trail edges of paper

## Xerox® VersaLink® C9000 Color Printer

<p><b>Print Features</b></p>	<p>Application Defaults            Banner Pages Enable / Disable            Bi-directional Real-time Status            Booklet Layout            Color Adjustments (lightness, contrast, saturation, color balance)            Color Correction            Draft Mode            Finishing (requires finishing)            Fit to new paper size            Job Identification (Print ID or Banner, Print ID in margins on first page only or all pages)            Job Monitoring (Client or Local User Interface)            N-up Page Layout (up to 16 pages per sheet)            Paper Selection by Attribute            Personal Print            Print Around Enable / Disable            Print from USB            Run Black            Sample Set            Saved Job            Scaling            Secure Print            Skip Blank Pages            Special Pages (exception page programming: covers, inserts, exceptions pages)            Store and Recall Driver Settings            Stored Jobs Deletion            Two-sided Printing (as default)            Watermark (predefined and custom)            Xerox® Earth Smart Driver Settings</p>
<p><b>Print from USB</b></p>	<p>Allows walk-up printing from Type A USB port            Supports direct printing from computer via Type B USB port            Supported file formats: PDF, JPEG, TIFF, XPS, PDF/A</p>
<p><b>Operating Systems</b></p>	<p>Windows® 7, 8, 8.1, 10            Windows Server 2008 SP2, Server 2008 R2 SP1, Server 2012, Server 2012 R2, Server 2016, Server 2019            macOS® 10.11, 10.12, 10.13            Citrix®            Redhat® Enterprise Linux®            Fedora Core            IBM® AIX®            HP-UX®            Oracle® Solaris            SUSE®            SAP®            UNIX®            Note: For information about supported versions for the above operating systems, please visit our Drivers &amp; Downloads page and specify your device at <a href="http://www.support.xerox.com">www.support.xerox.com</a>.</p>
<p><b>Fonts</b></p>	<p>PostScript fonts: 136            PCL fonts: 83</p>
<p><b>Xerox® Mobile Express Driver®</b></p>	<p>Makes it easy for mobile users to find, use and manage Xerox® and non-Xerox® devices in every new location. Plug into a new network, and Mobile Express Driver automatically discovers available printers and provides status and capability information. Save a list of “favorite” printers for each location, store application print settings for use on any printer in any network, and greatly reduce mobile support calls to IT.</p>
<p><b>Xerox® Global Print Driver®</b></p>	<p>A truly universal print driver that lets IT administrators install, upgrade and manage Xerox® and non-Xerox® devices from a single driver. It provides a consistent, easy-to-use interface for end-users, reducing the number of support calls, and simplifying print services management.</p>
<p><b>Xerox® Pull Print Driver</b></p>	<p>Makes it easy for IT managers to qualify, deploy and manage all print devices using a single driver in a Pull Print environment. Uses a single queue and single driver. The Xerox® Pull Print Driver extends convenience across a broad range of printing assets. IT administrators no longer need to manage and configure multiple drivers. Used in conjunction with Equitrac Office®, Ysoft® SafeQ®, Pharos® and others.</p>

## Xerox® VersaLink® C9000 Color Printer

Mobile Solutions and Mobile Device Apps	
<b>Apple® AirPrint®</b>	Print email, photos and important office documents directly from an Apple iPhone® or iPad® with no drivers to install and no cables to connect. With AirPrint, an iPhone or iPad automatically locates and connects to the AirPrint-enabled device over the office Wi-Fi network.
<b>Google Cloud Print™</b>	Google Cloud Print connects print devices to the web, enabling users to print the applications they use every day from smartphones, tablets, Chromebook™ notebook computers and any other web-connected device.
<b>@PrintByXerox</b>	@PrintByXerox is a free service that allows secure printing from any email-enabled device (computer, phone, tablet, iOS, Android™, Google® Chromebook™ and more) to a Xerox® printer or MFP using a single email address with no IT intervention. No training is needed. End-users simply send attachments to the email address, and release them at the MFP panel.
<b>Xerox® Print Service Plug-in for Android™ (Free at Google Play™ Store)</b>	The Xerox® Print Service Plug-in for Android KitKat (4.4 or greater) devices streamlines mobile printing without third-party apps or additional print drivers. You can easily print photos, Web pages and documents when your mobile device is connected to printers using a wireless network. A robust print option set includes two-sided printing, stapling and secure code release. A free download is available from the Google Play™ store.
<b>Xerox® Workplace Suite and Xerox® Workplace Cloud</b>	Xerox® Workplace Solutions boost productivity and reduce costs with a modular print management and mobility solution. Control and manage your printer fleet while enabling mobile productivity with simplified workflows, convenience and security—for any brand printer, anywhere. Xerox® Workplace Solutions offer flexible license options to suit any size business with the ability to scale as you grow. <ul style="list-style-type: none"> <li>• Xerox® Workplace Suite: On site, your server</li> <li>• Xerox® Workplace Cloud: Simple setup, cloud administration</li> </ul> To learn more about the Xerox® Workplace Suite and Xerox® Workplace Cloud, visit <a href="http://www.xerox.com/mobility">www.xerox.com/mobility</a> .
Software Solutions	
<b>Xerox® ConnectKey® Apps (Found at the Xerox® App Gallery)</b>	Increase user productivity by simplifying and shortening everyday tasks. Unlike traditional software, ConnectKey Apps do not require a dedicated server, PC or IT resource. Instead, simply download these lightweight, Serverless ConnectKey Apps to the device.
Security	
<b>Security Features</b>	Access Controls AES 256-bit Encryption Audit Log Certificate Path Validation Certificate Revocation List (CRL)/Status Protocol (OCSP) Detection of external program falsification (XCP Plug-in) Cisco® Identity Services Engine (ISE) Integration Domain Filtering FIPS 140-2 Firmware Verification Immediate Disk Overwrite IP Address Filtering IPsec Network Authentication Port Filtering Pre-installed Self-Signed Certificates Role Based Permissions Secure Print Security Certificate Management Smart Card Enablement (CAC/PIV/.NET) SNMPv3 Status Protocol (OCSP) TLS/SSL

## Xerox® VersaLink® C9000 Color Printer

Accounting	
<b>Xerox® Standard Accounting / Network Accounting (Standard)</b>	
<b>Tracking</b>	Print usage
<b>Accounting</b>	<p><b>Xerox® Standard Accounting Tool</b> Up to 9,999 User Accounts Up to 500 General accounts</p> <p><b>Network Accounting (Job Based Accounting)</b> Up to 60,000 User IDs; Up to 60,000 Account IDs Up to 14,000 accounting records (transactions)</p>
<b>Features</b>	Administrator can manage the feature via the Embedded Web Server.
<b>Accounting Options – Network Accounting (Allows central server to manage all accounting)</b>	
	<ul style="list-style-type: none"> <li>• Enhanced network accounting with up to the minute data on how the system is being used</li> <li>• Comprehensive management and enterprise scale tracking and reporting of device print usage</li> <li>• Numerous solutions are available through Xerox Alliance Partners. For details visit <a href="http://www.xerox.com">www.xerox.com</a></li> <li>• Security enhancements include simultaneous support for HTTP/HTTPS protocols</li> <li>• Device requests account authentication from third party server enabling larger databases of users and accounts</li> <li>• Accept Authentication Login at control panel and pass to third party Networking Account</li> </ul>
Paper Handling	
<b>Bypass Tray</b>	
<b>Capacity<sup>4</sup></b>	100 sheets
<b>Sizes</b>	Custom sizes: 3.5 x 3.9 in. to 12.6 x 19 in./88.9 x 98.4 mm to 320 x 482.6 mm Banners: 3.5 x 3.9 in. to 12.6 x 52 in./88.9 x 98.4 mm to 320 x 1320.8 mm
<b>Weights</b>	Simplex: 18 lb. bond to 130 lb. cover/64 to 350 gsm Duplex: 18 lb. bond to 110 lb. cover/64 to 300 gsm
<b>Types</b>	Bond Plain Paper Cardstock Custom Envelopes Extra Heavyweight Cardstock Extra Heavyweight Glossy Cardstock Glossy Cardstock Hole Punched Labels Heavyweight Cardstock Heavyweight Glossy Cardstock Letterhead Lightweight Cardstock Lightweight Glossy Cardstock Pre-Printed Postcards Recycled
<b>Tray 1 and 2</b>	
<b>Capacity<sup>4</sup></b>	520 sheets each
<b>Sizes</b>	Tray 1: 3.9 x 5.8 in. to 11.7 x 17 in./100 x 148 mm to 297 x 431.8 mm Tray 2: 3.9 x 5.8 in. to 12.6 x 18 in./100 x 148 mm to 320 x 457.2 mm
<b>Weights</b>	18 lb. bond to 110 lb. cover/64 to 300 gsm

# Xerox® VersaLink® C9000 Color Printer

<b>Types</b>	<ul style="list-style-type: none"> <li>Bond</li> <li>Plain Paper</li> <li>Cardstock</li> <li>Custom</li> <li>Envelopes</li> <li>Glossy Cardstock</li> <li>Hole Punched</li> <li>Labels</li> <li>Heavyweight Cardstock</li> <li>Heavyweight Glossy Cardstock</li> <li>Letterhead</li> <li>Lightweight Cardstock</li> <li>Lightweight Glossy Cardstock</li> <li>Pre-Printed</li> <li>Recycled</li> </ul>
<b>Two Tray Module</b>	
<b>Capacity<sup>4</sup></b>	1,040 sheets
<b>Sizes</b>	Custom sizes: 3.9 x 5.8 in. to 12.6 x 18 in./100 x 148 mm to 320 x 457.2 mm
<b>Weights</b>	18 lb. bond to 110 lb. cover/64 to 300 gsm
<b>Types</b>	<ul style="list-style-type: none"> <li>Bond</li> <li>Plain Paper</li> <li>Cardstock</li> <li>Custom</li> <li>Envelopes</li> <li>Glossy Cardstock</li> <li>Hole Punched</li> <li>Labels</li> <li>Heavyweight Cardstock</li> <li>Heavyweight Glossy Cardstock</li> <li>Letterhead</li> <li>Lightweight Cardstock</li> <li>Lightweight Glossy Cardstock</li> <li>Pre-Printed</li> <li>Recycled</li> </ul>
<b>Tandem Tray Module</b>	
<b>Capacity<sup>4</sup></b>	2,000 sheets
<b>Sizes</b>	8.5 x 11 in., 7.25 x 10.5 in./A4, B5
<b>Weights</b>	18 lb. bond to 110 lb. cover/64 to 300 gsm
<b>Types</b>	<ul style="list-style-type: none"> <li>Bond</li> <li>Plain Paper</li> <li>Cardstock</li> <li>Custom</li> <li>Envelopes</li> <li>Glossy Cardstock</li> <li>Hole Punched</li> <li>Labels</li> <li>Heavyweight Cardstock</li> <li>Heavyweight Glossy Cardstock</li> <li>Letterhead</li> <li>Lightweight Cardstock</li> <li>Lightweight Glossy Cardstock</li> <li>Pre-Printed</li> <li>Recycled</li> </ul>

## Xerox® VersaLink® C9000 Color Printer

High Capacity Feeder	
Capacity <sup>4</sup>	2,000 sheets
Sizes	8.5 x 11 in., 7.25 x 10.5 in./A4, B5
Weights	18 lb. bond to 95 lb. cover/64 to 216 gsm
Types	Bond Plain Paper Cardstock Custom Glossy Cardstock Hole Punched Labels Letterhead Lightweight Cardstock Lightweight Glossy Cardstock Pre-Printed Recycled
Envelope Tray – Replaces Tray 1 (Optional)	
Capacity <sup>4</sup>	Up to 50 envelopes
Sizes	#10 commercial, Monarch, DL, C4, C5, C6 Custom sizes: 3.5 x 3.85 in. to 9.5 x 13.1 in./90 x 98 mm to 241 x 332 mm
Total Capacity	
VersaLink C9000/DT Capacity <sup>4</sup>	1,140 sheets
Maximum Capacity <sup>4</sup>	5,140 sheets
Finishing	
Output Trays	
Catch Tray	500 sheets (without center tray) 2x 250 sheets (with center tray when offset is off) 2x 125 sheets (with center tray when offset is on)
Office Finisher (Optional)	
Capacity <sup>4</sup>	Stacking Tray: 2,000 sheets unstapled or 1,000 sheets single stapled or 750 sheets dual stapled (8.5 x 11 in. / A4) (dual stapling only with optional booklet maker) Offset available for collated sets of standard size paper (8.5 x 11 in. / A4 to 11 x 17 in. / A3)
Sizes	8.3 x 7.2 in. to 11.7 x 17 in./210 x 182 mm to 297 x 432 mm
Weights	16 lb. bond to 80 lb. cover/60 to 220 gsm
Multiposition Stapling	50 sheets of 24 lb. bond/90 gsm
Hole Punch (Optional) North America: Europe:	Up to 65 lb cover (200 gsm) available to the right center tray 2/3 hole punch 2/4 hole punch
Booklet Maker for Office Finisher (Score/Crease, Saddle-stitch Staple) (Optional)	
Capacity <sup>4</sup>	40 booklets (2-15 sheets per booklet – 20 lb. / 80 gsm or less)
Sizes	Letter – 8.5 x 11 in. / A4 SEF Legal – 8.5 x 14 in. / B4 SEF Ledger – 11 x 17 in. / A3 SEF
Saddle-stitch Stapling	2-15 sheets / 8-60 page booklet 16 lb. bond to 24 lb. bond / 60 to 90 gsm
Score / Crease	1-15 sheets / unstapled / 60-105 gsm only



## Xerox® VersaLink® C9000 Color Printer

Optional BR Booklet Maker Finisher (Requires Horizontal Transport Kit)	
<b>Capacity<sup>4</sup></b>	Offsetting Top Tray: 500 sheets of 8.5 x 11 in./A4 unstapled Stacking Stapling Tray: 1,500 sheets of 8.5 x 11 in./11 x 17 in./A4/A3 unstapled or 200 stapled sets of 8.5 x 11 in./A4 (single-position stapling or dual or 4-position stapling) or 100 stapled sets of 11 x 17 in./A3
<b>Sizes</b>	4 x 6 in. to 11 x 17 in./A6 to A3 for stacking 7.25 x 10.5 in. to 11 x 17 in./B5 to A3 for stapling
<b>Weights</b>	16 bond to 110 lb. cover/60 to 300 gsm (coated and uncoated)
<b>Stapling</b>	Single and multiposition stapling Auto stapling (50 sheets maximum) – 24 lb. / 90 gsm Letter, Legal, Tabloid, A3, A4, B4 and B5 sizes supported
<b>Hole Punch</b> North America Europe	2/3 hole punch 2/4 hole punch 4 hole “Swedish” punch (optional)
<b>Booklet Maker</b>	Saddle-stitch 2 to 16 sheets (7 sheets at 106 to 176 gsm coated or 5 sheets at 177 to 220 gsm coated) Bi-fold up to 5 sheets Letter, Legal, Tabloid, A3, A4 supported
Device Management	
<b>Network Protocols</b>	TCP/IP: HTTP/HTTPS, Internet Printing Protocol, LPR/LPD, Raw Socket Printing/Port 9100, IPv4/IPv6, WSD LDAP Bonjour® / AirPrint™ Most protocols not in use can be disabled
<b>Administrative Protocols</b>	DHCP, SNMP, WINS, HTTP, HTTPS, TLS, SNTP, MDNS
Xerox® CentreWare® Web	
	<ul style="list-style-type: none"> <li>• A Web-based server application for network administrators that permits web browser-based device management from any workstation, whether running Windows or UNIX or any other operating system</li> <li>• Works with any SNMP-managed printer from any manufacturer</li> <li>• Provides help with device discovery and installations, health checks and troubleshooting, and device upgrades, as well as basic accounting and asset management</li> </ul>
Xerox® Embedded Web Server – Integrated Device Web Page	
<b>Device Status</b>	<ul style="list-style-type: none"> <li>• Tray status/contents</li> <li>• Consumables status</li> <li>• Billing/Usage</li> <li>• Quick Links</li> <li>• Online Support</li> </ul>
<b>Print Queue Viewing</b>	Job print queue management—view and delete
<b>Job Submission</b>	Print-ready files (PS, PCL, PDF, XPS, JPEG, TXT, PRN, TIF)
<b>Device Administration</b>	Allows simple, remote installation setting of configuration options and management of the device
<b>Browsers</b>	Microsoft® Internet Explorer® Microsoft Edge™ Mozilla™ Firefox® Apple® Safari® Google Chrome™

## Xerox® VersaLink® C9000 Color Printer

Remote Services		
<b>Xerox® MeterAssistant® Service</b>	Automates the process of collecting and submitting meter reads for tracking and billing of Xerox® device usage. Eliminates the need for time-consuming end-user involvement and ensures that meter reads are submitted to Xerox on time.	
<b>Xerox® SuppliesAssistant® Service</b>	Automatically orders supplies for Xerox® output devices based on actual usage, eliminating the need to manually manage supplies inventory.	
<b>MaintenanceAssistant Service</b>	Offers a fast (and free) way to resolve potential issues and receive assistance and automate the troubleshooting/repair process. Diagnostic data is sent to Xerox, allowing for problems to be solved faster with increased uptime.	
What's In The Box		
	<ul style="list-style-type: none"> <li>• VersaLink C9000 Color Printer</li> <li>• Starter Capacity Print Cartridge: One of each (Cyan, Magenta, Yellow: 12,000 print capacity<sup>5</sup>, Black: 18,000 print capacity<sup>5</sup>)</li> <li>• Drum Cartridge – One of each (Cyan, Magenta, Yellow, and Black 190,000 print capacity)<sup>6</sup></li> <li>• Quick Use Guide</li> <li>• Install Guide</li> <li>• Software and Documentation CD (with Drivers, Warranty Statement and Safety Regulatory Recycle Disposal Guide)</li> <li>• Power Cord</li> </ul>	
Supplies and Accessories	Quantity	Part Number
Supplies		
<b>Standard Capacity Toner Cartridges</b>	Cyan: 12,300 standard pages <sup>5</sup> Magenta: 12,300 standard pages <sup>5</sup> Yellow: 12,300 standard pages <sup>5</sup> Black: 18,900 standard pages <sup>5</sup>	106R04062 106R04063 106R04064 106R04065
<b>High Capacity Toner Cartridges</b>	Cyan: 26,500 standard pages <sup>5</sup> Magenta: 26,500 standard pages <sup>5</sup> Yellow: 26,500 standard pages <sup>5</sup> Black: 31,400 standard pages <sup>5</sup>	106R04074 106R04075 106R04076 106R04077
<b>Drum Cartridge</b>	Cyan: 190,000 standard pages <sup>6</sup> Magenta: 190,000 standard pages <sup>6</sup> Yellow: 190,000 standard pages <sup>6</sup> Black: 190,000 standard pages <sup>6</sup>	101R00602
<b>Waste Cartridge</b>	47,000 standard pages <sup>6</sup>	108R01504
<b>IBT Cleaner</b>	160,000 standard pages <sup>6</sup>	104R00256
<b>Transfer Roller</b>	200,000 standard pages <sup>6</sup>	116R00015
<b>Office Finisher Booklet Maker Cartridge (8 cartridges per container)</b>	16,000 staples (2,000 each cartridge)	008R12897
<b>Staple Refills for Office Finisher (3 refills per container)</b>	15,000 staples (5,000 each refill)	008R12941
<b>Staple Cartridges for BR Finisher and Office Finisher (1 cartridge per carton)</b>	5,000 staples (5,000 each cartridge)	008R12964
<b>Staple Cartridges for BR Booklet Maker (1 cartridge per carton)</b>	5,000 staples (5,000 each cartridge)	008R13177

## Xerox® VersaLink® C9000 Color Printer

Accessories / Options	
Two Tray Module	097S04969
Tandem Tray Module	097S04970
High Capacity Feeder	097S04845
Envelope Tray (Replaces Tray 1)	497K17880
Office Finisher Gap Filler (required)	097S04848 497K17370
2/3 Hole Punch for Office Finisher	497K03860
2/4 Hole Punch for Office Finisher	497K03870
Booklet Maker for Office Finisher	497K03852
BR Booklet Maker Finisher with 2/3 Hole Punch	097S04981
BR Booklet Maker finisher with 2/4 Hole Punch	097S04982
Horizontal Transport for BR Finisher	497K17440
Swedish 4 Hole Punch for BR Finisher	497K14370
Wireless Network Adapter Kit	497K16750
Xerox Precise Color Management System	097S04974
Internal Card Reader/RFID Kit	497K18120 (Western Hemisphere) 497K18140 (Eastern Hemisphere)

<sup>1</sup> Maximum volume capacity expected in any one month. Not expected to be sustained on a regular basis.

<sup>2</sup> Expected regular monthly throughput.

<sup>3</sup> Power states defined per ENERGY STAR® Program requirements for Imaging Equipment.

<sup>4</sup> Paper capacities are based on 20 lb. 75 gsm stock; capacities will vary with different weight stocks.

<sup>5</sup> Average standard pages. Declared Yield in accordance with ISO/IEC 19798. Yield will vary based on image, area coverage and print mode.

<sup>6</sup> Approximate pages. Declared yield will vary depending on job run length, media size/orientation and machine speed. For more information visit: <http://www.office.xerox.com/latest/SUPGL-01.pdf>.

Return spent imaging supplies through the Xerox® Green World Alliance® collection/reuse/recycling program. For more information, visit [www.xerox.com/about-xerox/recycling](http://www.xerox.com/about-xerox/recycling).

For more information, visit us at [www.xerox.com/office](http://www.xerox.com/office).

Configurations vary by geography.